
# TDA7365

## 2 x 6W CAR RADIO AMPLIFIER PLUS SOLID STATE SWITCH

- OUTPUT POWER 2x6W/4Ω @14.4V, 1KHz, 10%
- SOLID STATE POWER SWITCH INCLUDED (1A @ $V_{DROP}$ = 0.8V Typ.)
- MINIMUM EXTERNAL COMPONENT COUNT
  - INTERNALLY FIXED GAIN (40dB)
  - NO BOOTSTRAP CAPACITORS
  - NO EXTERNAL COMPENSATION
- ST-BY FUNCTION (CMOS COMPATIBLE)
- MUTE FUNCTION (CMOS COMPATIBLE)
- NO AUDIBLE POP DURING MUTE/ST-BY OPERATIONS
- LOW SUPPLY SELF MUTING

**PROTECTIONS**

- AC AUDIO OUTPUTS SHORT CIRCUIT TO GND
- DC AUDIO OUTPUTS SHORT CIRCUIT TO GND AND TO $V_S$ AT POWER ON
- SWITCH OUTPUT INTERNAL CURRENT LIMITATION
- OVERRATING CHIP TEMPERATURE WITH SOFT THERMAL LIMITER
- LOAD DUMP
- FORTUITOUS OPEN GND




**MULTIWATT15**
**ORDERING NUMBER:** TDA7365

- REVERSE BATTERY
- ESD

**DESCRIPTION**


The TDA7365 is a new technology Dual Audio Amplifier in Multiwatt15 package especially designed for stereo car radio applications.
Thanks to the fully complementary output configuration the TDA7365 delivers a rail to rail voltage swing with no need of boostrap capacitors
It includes a solid state switch, enabled by a ST-BY function common to the audio section, suitable for supplying both the signal processing part of the car radio set and the lamps. As a results the power-on operation is simplified, thereby saving cost and space in the whole power section.

**BLOCK DIAGRAM**




Obsolete Product(s) - Obsolete Product(s)

**PIN CONNECTION** (Top view)




Obsolete Product(s) - Obsolete Product(s)

## ABSOLUTE MAXIMUM RATINGS

| Symbol | Parameter | Value | Unit |
|---|---|---|---|
| $V_S$ | DC Supply Voltage | 28 | V |
| $V_{OP}$ | Operating Supply Voltage | 18 | V |
| $V_{PEAK}$ | Peak Supply Voltage (t = 50ms) | 40 | V |
| $I_O$ | Audio Channels Output Peak Current (not rep. t = 100µs) | 4 | A |
| $I_O$ | Audio Channels Output Peak Current (rep. f > 10Hz) | 3 | A |
| $I_O$ | Switch Output Peak Current | (internally limited) 1.5 | A |
| $P_{tot}$ | Power Dissipation ($T_{case}$ = 85°C) | 32 | W |
| $T_{stg}$, $T_j$ | Storage and Junction Temperature | -40 to 150 | °C |

## THERMAL DATA

| Symbol | Description | | Value | Unit |
|---|---|---|---|---|
| $R_{th\ j\text{-}case}$ | Thermal Resistance Junction-case | Max | 2 | °C/W |

**ELECTRICAL CHARACTERISTICS** (Refer to the test circuit; $V_S$ = 14.4V; $R_L$ = 4Ω, $T_{amb}$ = 25°C, f = 1kHz, unless otherwise specified)


| Symbol | Parameter | Test Condition | Min. | Typ. | Max. | Unit |
|---|---|---|---|---|---|---|
| $V_S$ | Supply Range | | 8 | | 18 | V |
| $I_d$ | Total Quiescent Drain Current | Power Switch Unloaded | | 80 | | mA |
| $P_O$ | Output Power | $R_L$ = 4Ω; THD = 10% each channel | 5.5 | 6 | | W |
| | | $R_L$ = 2Ω; THD = 10% each channel | | 9 | | W |
| d | Distortion | $P_O$ = 0.1 to 3W | | 0.08 | 0.3 | % |
| CT | Cross Talk | f = 1kHz; $R_g$ = 0<br>f = 10kHz; $R_g$ = 0 | 50 | 55<br>50 | | dB<br>dB |
| $R_{IN}$ | Input Impedance | | 40 | 50 | | KΩ |
| $G_V$ | Voltage Gain | | 39 | 40 | 41 | dB |
| $G_V$ | Voltage Gain Match. | | | | 1 | dB |
| $E_{IN}$ | Input Noise Voltage (*) | Rg = 0 | | 1.2 | 5 | µV |
| SVR | Supply Voltage Rejection | $R_g$ = 0 ; f = 100Hz;<br>$V_r$ = 0.5$V_{rms}$ | 45 | 50 | | dB |
| ASB | Stand-by Attenuation | | 60 | 90 | | dB |
| $I_{SB}$ | ST-BY Current Consumption | | | | 100 | µA |
| $V_{SB\ IN}$ | ST-BY IN Threshold Voltage | | | | 1.5 | V |
| $V_{SB\ OUT}$ | ST-BY OUT Threshold Voltage | | 3.5 | | | V |
| $V_{M\ IN}$ | MUTE IN Threshold Voltage | | | | 1.5 | V |
| $V_{M\ OUT}$ | MUTE OUT Threshold Voltage | | 3.5 | | | V |

## POWER SWITCH CHARACTERISTICS

| Symbol | Parameter | Test Condition | Min. | Typ. | Max. | Unit |
|---|---|---|---|---|---|---|
| $I_{Op}$ | Continuous Output Current | | | 1.2 | | A |
| $V_{DROP}$ | Dropout Voltage | Io = 1A | | | 1.4 | V |

(*) 22Hz to 22KHz
(**) A weighted

## TEST AND APPLICATION CIRCUIT




Obsolete Product(s) - Obsolete Product(s)

**Figure 1:** P.C.Board and component layout of the Test and Application Circuit 1:1 scale.





**Figure 2:** Quiescent Drain Current vs. Supply Voltage





**Figure 3:** Output Power vs. Supply Voltage





**Figure 4:** Output Power vs. Supply Voltage






**Figure 5:** Distortion vs. Output Power




Obsolete Product(s) - Obsolete Product(s)

**Fiigure 6:** Distortion vs. Frequency






**Figure 7:** Supply Voltage Rejection




**Fiigure 8:** Cross-Talk vs. Frequency





**Figure 9:** Switch Drop-out vs. Switch Current





**Figure 10:** Total Power Dissipation and Efficiency vs. Output Power







**Figure 11:** Total Power Dissipation and Efficiency





Obsolete Product(s) - Obsolete Product(s)

| DIM. | mm | | | inch | | |
|---|---|---|---|---|---|---|
| | MIN. | TYP. | MAX. | MIN. | TYP. | MAX. |
| A | | | 5 | | | 0.197 |
| B | | | 2.65 | | | 0.104 |
| C | | | 1.6 | | | 0.063 |
| D | | 1 | | | 0.039 | |
| E | 0.49 | | 0.55 | 0.019 | | 0.022 |
| F | 0.66 | | 0.75 | 0.026 | | 0.030 |
| G | 1.02 | 1.27 | 1.52 | 0.040 | 0.050 | 0.060 |
| G1 | 17.53 | 17.78 | 18.03 | 0.690 | 0.700 | 0.710 |
| H1 | 19.6 | | | 0.772 | | |
| H2 | | | 20.2 | | | 0.795 |
| L | 21.9 | 22.2 | 22.5 | 0.862 | 0.874 | 0.886 |
| L1 | 21.7 | 22.1 | 22.5 | 0.854 | 0.870 | 0.886 |
| L2 | 17.65 | | 18.1 | 0.695 | | 0.713 |
| L3 | 17.25 | 17.5 | 17.75 | 0.679 | 0.689 | 0.699 |
| L4 | 10.3 | 10.7 | 10.9 | 0.406 | 0.421 | 0.429 |
| L7 | 2.65 | | 2.9 | 0.104 | | 0.114 |
| M | 4.25 | 4.55 | 4.85 | 0.167 | 0.179 | 0.191 |
| M1 | 4.63 | 5.08 | 5.53 | 0.182 | 0.200 | 0.218 |
| S | 1.9 | | 2.6 | 0.075 | | 0.102 |
| S1 | 1.9 | | 2.6 | 0.075 | | 0.102 |
| Dia1 | 3.65 | | 3.85 | 0.144 | | 0.152 |

## OUTLINE AND MECHANICAL DATA



**Multiwatt15 V**




Obsolete Product(s) - Obsolete Product(s)

Obsolete Product(s) - Obsolete Product(s)

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a registered trademark of STMicroelectronics.

All other names are the property of their respective owners

© 2003 STMicroelectronics - All rights reserved

**STMicroelectronics GROUP OF COMPANIES**

Australia – Belgium - Brazil - Canada - China – Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States

**www.st.com**

**ООО «НИОКРсистемс» -** это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

## Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование
- Работаем по 275 ФЗ

ООО «НИОКР СИТЕМС»
Москва, 125362, Россия, ул. Вишневая, д. 9, к. 1, Блок 104 а и 104 в

Телефон: 8 (495) 268-14-82
Email: n@nsistems.ru

ИНН: 7735154786
ОГРН: 1167746717709