
| VACUUMSCHMELZE | SPECIFICATION | Item no.: T60404-N4646-X412 |
|---|---|---|

K-No.: 24618

**50/100 A Current Sensor**

For the electronic measurement of currents:
DC, AC, pulsed, mixed ..., with a galvanic
Isolation between the primary circuit
(high power) and the secondary circuit
(electronic circuit)



Date: 28.01.2008

Customer: Standard type | Customers Part no.: | Page 1 of 2

**Description**

- Closed loop (compensation) Current Sensor with magnetic field probe
- Printed circuit board mounting
- Casing and materials UL-listed

**Characteristics**

- Excellent accuracy
- Very low offset current
- Very low temperature dependency and offset current drift
- Very low hysteresis of offset current
- Low response time
- Wide frequency bandwidth
- Compact design
- Reduced offset ripple

**Applications**

Mainly used for stationary operation in industrial applications:

- AC variable speed drives and servo motor drives
- Static converters for DC motor drives
- Battery supplied applications
- Switched Mode Power Supplies (SMPS)
- Power Supplies for welding applications
- Uninterruptable Power Supplies (UPS)

## Electrical data – Ratings[1)]

| | | | |
|---|---|---|---|
| $I_{PN}$ | Primary nominal r.m.s. current | | |
| | @ $V_C$ = ±15V, $R_M$ ≥ 0 Ω | 50 | A |
| | @ $V_C$ = ±12V, $R_M$ ≥ 0 Ω or $V_C$ = ±15V, $R_M$ ≥ 16 Ω | 100 | A |
| $R_M$ | Measuring resistance $V_C$=± 12V | 0 ... 200 | Ω |
| | $V_C$=± 15V | 16 … 400 | Ω |
| $I_{SN}$ | Secondary nominal r.m.s. current | 25/50 | mA |
| $K_N$ | Turns ratio | 1…3 : 2000 | |

## Accuracy – Dynamic performance data[1)]

| | | min. | typ. | max. | Unit |
|---|---|---|---|---|---|
| $I_{P,max}$ | Max. measuring range | | | | |
| | @ $V_C$ = ±12V, $R_M$ = 10 Ω ($t_{max}$ = 10sec) | ±145 | | | A |
| | @ $V_C$ = ±15V, $R_M$ = 16 Ω ($t_{max}$ = 10sec) | ±175 | | | A |
| X | Accuracy @ $I_{PN}$, $T_A$= 25°C | | 0.1 | 0.5 | % |
| $\varepsilon_L$ | Linearity | | | 0.1 | % |
| $I_0$ | Offset current @ $I_P$=0, $T_A$= 25°C | | 0.02 | 0.08 | mA |
| $t_r$ | Response time | | 500 | | ns |
| Δt ($I_{P,max}$) | Delay time at di/dt = 100 A/µs | | 200 | | ns |
| f | Frequency bandwidth | DC...200 | | | kHz |

## General data[1)]


| | | min. | typ. | max. | Unit |
|---|---|---|---|---|---|
| $T_A$ | Ambient operating temperature | -40 | | +85 | °C |
| $T_S$ | Ambient storage temperature | -40 | | +90 | °C |
| m | Mass | | 13,5 | | g |
| $V_C$ | Supply voltage | ±11.4 | ±12 or ±15 | ±15.75 | V |
| $I_C$ | Current consumption | | 18.5 | | mA |
| | Constructed and manufactored and tested in accordance with EN 61800-5-1 (Pin 1 - 6 to Pin 7 – 9) Reinforced insulation, Insulation material group 1, Pollution degree 2 | | | | |
| $S_{clear}$ | clearance (component without solder pad) | 10.2 | | | mm |
| $S_{creep}$ | creepage (component without solder pad) | 10.2 | | | mm |
| $V_{sys}$ | System voltage overvoltage category 3 | RMS | | 600 | V |
| $V_{work}$ | Working voltage (table 7 acc. to EN61800-5-1) | RMS | | 1020 | V |
| $U_{PD}$ | Rated discharge voltage | peak value | | 1400 | V |

| Date | Name | Isuue | Amendment |
|---|---|---|---|
| 28.01.08 | Le | 81 | Date changed. Insignificant |
| | | | |

| Hrsg.: KB-E editor | Bearb: SA designer | | KB-E BE: Len. check | KB-PM IA: KRe. check | | freig.: Heu. released |
|---|---|---|---|---|---|---|


Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden
Any offenders are liable to pay all relevant damages.

| VACUUMSCHMELZE | **SPECIFICATION** | **Item no.:** | **T60404-N4646-X412** |
|---|---|---|---|

| K-No.: 24618 | **50/100 A Current Sensor**<br>For the electronic measurement of currents:<br>DC, AC, pulsed, mixed ..., with a galvanic<br>Isolation between the primary circuit<br>(high power) and the secondary circuit<br>(electronic circuit) |  | Date: 28.01.2008 |
|---|---|---|---|

| Customer: Standard type | Customers Part no.: | Page 2 of 2 |
|---|---|---|

**Mechanical outline (mm):** General tolerances DIN ISO 2768-c







DC = Date Code
F= Factory

Connections:
1...6: ∅ 1,5 mm
7...9: 0,6x0,7 mm




Marking:

4646X412
F DC

**Schematic diagram**




**Possibilities of wiring for $V_C$ = ±15V** [1] (@ $T_A$ = 85°C, $R_M$ = 25 Ω)

| primary windings $N_P$ | primary current RMS $I_P$ [A] | primary current maximal $\hat{I}_{P,max}$ [A] | output current RMS $I_S$ ($I_P$) [mA] | turns ratio $K_N$ | primary resistance $R_P$ [mW] | wiring |
|---|---|---|---|---|---|---|
| 1 | 100 | 175 | 50 | 1:2000 | 0.12 |  |
| 2 | 35 | 82 | 35 | 2:2000 | 0.54 |  |
| 3 | 25 | 58 | 37,5 | 3:2000 | 1.1 |  |


[1] preliminary data

Temperature of the primary conductor should not exceed 100°C.
Additional information is obtainable on request.
This specification is no declaration of warranty acc. BGB §443 dar.

| Hrsg.: KB-E<br>editor | Bearb: SA<br>designer | | KB-E BE: Len.<br>check | KB-PM IA: KRe.<br>check | | freig.: Heu.<br>released |
|---|---|---|---|---|---|---|

Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden
Any offenders are liable to pay all relevant damages.

| VACUUMSCHMELZE | **Additional Information** | **Item No.:** | **T60404-N4646-X412** |
|---|---|---|---|

| K-No.: 24618 | **50/100 A Current Sensor**<br>For electronic current measurement:<br>DC, AC, pulsed, mixed ..., with a galvanic isolation between primary circuit (high power) and secondary circuit |  | Date: 28.01.2008 |
|---|---|---|---|

| Customer: | Customers Part No.: | Page 1 of 3 |
|---|---|---|

**Electrical Data (investigate by a type checking)** [1)]

| | | min. | typ. | max. | Unit |
|---|---|---|---|---|---|
| $V_{Ctot}$ | Maximum supply voltage (without function)<br>±15.75 bis ±18 V: for 1s per hour | | | ±18 | V |
| $R_S$ | Secondary coil resistance @ $T_A$=85°C | | | 145 | Ω |
| $R_p$ | Primary coil resistance per turn @ $T_A$=25°C | | | 0.36 | mΩ |
| $X_{Ti}$ | Temperature drift of X @ $T_A$ = -40 ... +85 °C | | | 0.1 | % |
| $I_{0ges}$ | Offset current (including $I_0$, $I_{0t}$, $I_{0T}$) | | | 0.1 | mA |
| $I_{0t}$ | Long term drift Offset current $I_0$ | | 0.03 | | mA |
| $I_{0T}$ | Offset current temperature drift $I_0$ @ $T_A$ = -40 ...+85°C | | 0.03 | | mA |
| $I_{0H}$ | Hyteresis current @ $I_P$=0 (caused by primary current 3 x $I_{PN}$) | | 0.02 | 0.05 | mA |
| $\Delta I_0/\Delta V_C$ | Supply voltage rejection ratio | | | 0.01 | mA/V |
| $i_{oss}$ | Offset ripple* (with1 MHz- filter first order) | | | 0.15 | mA |
| $i_{oss}$ | Offset ripple* (with 100 kHz- filter first order) | | 0.017 | 0.025 | mA |
| $i_{oss}$ | Offset ripple* (with 20 kHz- filter first order) | | 0.005 | 0.007 | mA |
| $C_k$ | Maximum possible coupling capacity (primary – secondary) | | 5 | | pF |
| | Mechanical Stress according to M3209/3<br>Settings: 10 – 2000 Hz, 1 min/Decade, 2 hours<br>An exceptionally high rate of on/off – switching of the supply voltage accelerates the aging process of the sensor. | | | 10g | |

**Inspection**[1)] (Measurement after temperature balance of the samples at room temperature)

| | | | | | |
|---|---|---|---|---|---|
| $K_N(N_1/N_2)$ | (V) | M3011/6 | Transformation ratio ($I_P$=3*10A, 40-80 Hz) | 1…3 : 2000 ± 0.5 | % |
| $I_0$ | (V) | M3226 | Offset current | < 0.05 | mA |
| $V_{P,eff}$ | (V) | M3014 | Test voltage, rms, 1s<br>Pin 1 - 6 to Pin 7 - 9 | 2.5 | kV |
| $V_e$ | (AQL 1/S4) | | Partial discharge voltage acc. M3024 (RMS)<br>with $V_{vor}$ (RMS) | 1500<br>1875 | V<br>V |

**Type Testing** (Pin 1 - 6 to Pin 7 – 9)

Designed according standard EN 61800 with insulation material group 1


| | | | | |
|---|---|---|---|---|
| $V_W$ | HV transient test according (to M3064)<br>(1,2 µs / 50 µs-wave form) | | 8 | kV |
| $V_d$ | Testing voltage acc. M3014 (RMS) | (5 s) | 5 | kV |
| $V_e$ | Partial discharge voltage acc. M3024 (RMS)<br>with $V_{vor}$ (RMS) | | 1500<br>1875 | V<br>V |

| Datum | Name | Index | Änderung |
|---|---|---|---|
| 28.01.08 | Le | 81 | Page 3: write error in $X_{ges}$ ($I_{PN}$). changed. Insignificant |
| | | | |

| Hrsg.: KB-E<br>editor | Bearb: SA<br>designer | | KB-E BE: Len.<br>check | KB-PM IA:KRe.<br>check | | freig.: Heu.<br>released |
|---|---|---|---|---|---|---|

Weitergabe sowie Vervielfältigung dieser Unterlage, Verwertung und Mitteilung ihres Inhalts nicht gestattet, soweit nicht ausdrücklich zugestanden. Zuwiderhandlungen verpflichten zu Schadenersatz. Alle Rechte für den Fall der Patenterteilung oder GM-Eintragung vorbehalten


Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden. Any offenders are liable to pay all relevant damages.






## Limit curve of measurable current $\hat{I}_P(R_M)$ 1)

@ ambient temperature $T_A \leq 85$ °C




## Maximum measuring range (µs-range) 1)

Output current behaviour of a 3kA current pulse
@ $V_C = \pm 15V$ und $R_M = 25\Omega$




Fast increasing currents (higher than the specified $I_{p,max}$), e.g. in case of a short circuit, can be transmitted because the currents are transformed directly.

The offset ripple can be reduced by an external low pass. Simplest solution is a passive low pass filter of 1st order with

$$f_g = \frac{1}{2p \cdot R_M \cdot C_a}$$

In this case the response time is enlarged.
It is calculated from:

$$t_r' \leq t_r + 2{,}5 R_M C_a$$


## Applicable documents

Current direction: A positive output current appears at point $I_S$, by primary current in direction of the arrow.
Constructed and manufactored and tested in accordance with EN 61800.
Housing and bobbin material UL-listed: Flammability class 94V-0.



Weitergabe sowie Vervielfältigung dieser Unterlage, Verwertung und Mitteilung ihres Inhalts nicht gestattet, soweit nicht ausdrücklich zugestanden. Zuwiderhandlungen verpflichten zu Schadenersatz. Alle Rechte für den Fall der Patenterteilung oder GM-Eintragung vorbehalten

Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden. Any offenders are liable to pay all relevant damages.



$I_{0H}$: Zero variation of $I_o$ after overloading with a DC of tenfold the rated value ($R_M = R_{MN}$)

$I_{0t}$: Long term drift of $I_o$ after 100 temperature cycles in the range -40 bis 85 °C.

$t_r$: Response time (describe the dynamic performance for the specified measurement range), measured as delay time at $I_P = 0{,}9 \cdot I_{Pmax}$ between a rectangular current and the output current.

$\Delta t\ (I_{Pmax})$: Delay time (describe the dynamic performance for the rapid current pulse rate e.g short circuit current) measured between $I_{Pmax}$ and the output current $i_a$ with a primary current rise of $di_1/dt = 100$ A/µs.

$X_{ges}(I_{PN})$: The sum of all possible errors over the temperature range by measuring a current $I_{PN}$:

$$X_{ges} = 100 \cdot \left| \frac{I_S(I_{PN})}{K_N \cdot I_{PN}} - 1 \right| \%$$

X: Permissible measurement error in the final inspection at RT, defined by

$$X = 100 \cdot \left| \frac{I_{SB}}{I_{SN}} - 1 \right| \%$$

where $I_{SB}$ is the output DC value of an input DC current of the same magnitude as the (positive) rated current ($I_o = 0$ )

$X_{Ti}$: Temperature drift of the rated value orientated output term. $I_{SN}$ (cf. Notes on $F_i$) in a specified temperature range, obtained by:

$$X_{Ti} = 100 \cdot \left| \frac{I_{SB}(T_{A2}) - I_{SB}(T_{A1})}{I_{SN}} \right| \%$$

$\varepsilon_L$: Linearity fault defined by $e_L = 100 \cdot \left| \frac{I_P}{I_{PN}} - \frac{I_{Sx}}{I_{SN}} \right| \%$

Where $I_P$ is any input DC and $I_{Sx}$ the corresponding output term. $I_{SN}$: see notes of $F_i$ ($I_o = 0$).

This “Additional information“ is no declaration of warranty according BGB $443.



Weitergabe sowie Vervielfältigung dieser Unterlage, Verwertung und Mitteilung ihres Inhalts nicht gestattet, soweit nicht ausdrücklich zugestanden. Zuwiderhandlungen verpflichten zu Schadenersatz. Alle Rechte für den Fall der Patenterteilung oder GM-Eintragung vorbehalten

Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden. Any offenders are liable to pay all relevant damages.

**ООО «НИОКРсистемс» -** это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

## Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование
- Работаем по 275 ФЗ

ООО «НИОКР СИТЕМС»
Москва, 125362, Россия, ул. Вишневая, д. 9, к. 1, Блок 104 а и 104 в

Телефон: 8 (495) 268-14-82
Email: n@nsistems.ru

ИНН: 7735154786
ОГРН: 1167746717709