
- PERFORMANCE (1.8 GHz)
  - ♦ 40 dBm Output Power (P_{1dB})
  - ♦ 11 dB Power Gain (G_{1dB})
  - ♦ -44 dBc WCDMA ACPR at 30 dBm output power
  - ♦ 180 to 300 mA typical quiescent current (I_{DQ})
  - ♦ 55% Power-Added Efficiency
  - ♦ Evaluation Boards Available
  - ♦ Additional Design Data Available on Website
  - ♦ Usable Gain to 3.8GHz



SEE PACKAGE OUTLINE FOR MARKING CODE

- DESCRIPTION AND APPLICATIONS

The FPD10000AF is a packaged depletion mode AlGaAs/InGaAs pseudomorphic High Electron Mobility Transistor (pHEMT), optimized for power applications in L-Band. The high power flange-mount package has been optimized for low electrical parasitics and optimal heatsinking.

Typical applications include drivers or output stages in PCS/Cellular base station transmitter amplifiers, as well as other power applications in WLL/WLAN amplifiers.

- ELECTRICAL SPECIFICATIONS AT 22°C

Parameter	Symbol	Test Conditions	Min	Typ	Max	Units
RF SPECIFICATIONS MEASURED AT f = 1.8 GHz USING CW SIGNAL						
Power at 1dB Gain Compression Class B Operation	P_{1dB}	V_{DS} = 12V; I_{DQ} = 180 mA		40		dBm
Power Gain at dB Gain Compression	G_{1dB}	V_{DS} = 12V; I_{DQ} = 180 mA V_{DS} = 12V; I_{DQ} = 300 mA		10 11		dB
Maximum Stable Gain: S_{21}/S_{12} P_{IN} = 0dBm, 50Ω system	MSG	V_{DS} = 12 V; I_{DQ} = 180 mA V_{DS} = 12 V; I_{DQ} = 300 mA		16.5 18.0		dB
Power-Added Efficiency at 1dB Gain Compression	PAE	V_{DS} = 12V; I_{DQ} = 180 mA I_{RF} (drive-up current) ~ 1.5A		55		%
Adjacent Channel Power Ratio WCDMA BTS Forward (64 channels) 10.15 dB Pk/Avg 0.001%	ACPR	V_{DS} = 12V; I_{DQ} = 180 mA Channel power = 30 dBm		-44		dBc
Saturated Drain-Source Current	I_{DSS}	V_{DS} = 3.0 V; V_{GS} = 0 V		5.2		A
Gate-Source Leakage Current	I_{GSO}	V_{GS} = -3 V		3		mA
Pinch-Off Voltage	$\|V_P\|$	V_{DS} = 3.0 V; I_{DS} = 19 mA		1.1		V
Gate-Drain Breakdown Voltage	$\|V_{BDGD}\|$	I_{GD} = 19 mA	30	35		V
Thermal Resistivity (channel-to-case)	Θ_{CC}	See Note on following page		3.5		°C/W

- RECOMMENDED OPERATING BIAS CONDITIONS

  Drain-Source Voltage: From 10 to 12V
  Quiescent Current: From 180 (Class B) to 300 mA (Class AB) operation

- ABSOLUTE MAXIMUM RATINGS[1]

Parameter	Symbol	Test Conditions	Min	Max	Units
Drain-Source Voltage	V_{DS}	$-3V < V_{GS} < +0V$		16	V
Gate-Source Voltage	V_{GS}	$0V < V_{DS} < +15V$		-3	V
Drain-Source Current	I_{DS}	For $V_{DS} > 2V$		50% I_{DSS}	mA
Gate Current	I_G	Forward / Reverse current		+50/-8	mA
RF Input Power[2]	P_{IN}	Under any acceptable bias state		1.75	W
Channel Operating Temperature	T_{CH}	Under any acceptable bias state		175	ºC
Storage Temperature	T_{STG}	Non-Operating Storage	-40	150	ºC
Total Power Dissipation	P_{TOT}	See De-Rating Note below		42	W
Gain Compression	Comp.	Under any bias conditions		5	dB
Simultaneous Combination of Limits[3]		2 or more Max. Limits		80	%

[1] $T_{Ambient}$ = 22°C unless otherwise noted [2] Max. RF Input Limit must be further limited if input VSWR > 2.5:1
[3] Users should avoid exceeding 80% of 2 or more Limits simultaneously

Notes:

- Operating conditions that exceed the Absolute Maximum Ratings will result in permanent damage to the device.
- Total Power Dissipation defined as: $P_{TOT} \equiv (P_{DC} + P_{IN}) - P_{OUT}$, where:
  P_{DC}: DC Bias Power
  P_{IN}: RF Input Power
  P_{OUT}: RF Output Power
- Total Power Dissipation to be de-rated as follows above 22°C:
  $P_{TOT} = 42 - (0.286W/°C) \times T_{PACK}$
  where T_{PACK} = *source tab lead temperature above 22°C*
  (coefficient of de-rating formula is the Thermal Conductivity)

Example: For a 55°C Source flange temperature: $P_{TOT} = 42 - (0.286 \times (55 - 22)) = 32.6W$

- *Note on Thermal Resistivity:* The nominal value of 3.5°C/W is measured with the package mounted on a large heatsink with thermal compound to ensure adequate contact. The package temperature is referred to the Source flange.


- HANDLING PRECAUTIONS

To avoid damage to the devices care should be exercised during handling. Proper Electrostatic Discharge (ESD) precautions should be observed at all stages of storage, handling, assembly, and testing. These devices should be treated as Class 1A per ESD-STM5.1-1998, Human Body Model. Further information on ESD control measures can be found in MIL-STD-1686 and MIL-HDBK-263.

- BIASING GUIDELINES

  - Dual-bias (separate positive Drain and negative Gate supplies) circuits are recommended, requiring a regulated negative voltage supply for depletion-mode devices such as the FPD10000AF. The Gate bias supply should be capable of sinking / sourcing at least 10mA of current. The bias circuitry must be properly sequenced to ensure that the control Gate voltage (typically -0.6 to -1.0V) is applied to the device *before* the Drain voltage, otherwise large amounts of Drain-Source current will be drawn, potentially leading to instability and self-oscillation.
  - The recommended 180 – 300 mA bias point is nominally a Class B/AB mode. A small amount of RF gain expansion prior to the onset of compression is normal for this operating point, and significant current drive-up should be expected. If a Class A operation is desired, users should check the de-rating limits given in the previous section to ensure reliable operation.

- PACKAGE OUTLINE
  (dimensions in millimeters – mm)



PACKAGE MARKING CODE

Example:

***f*1ZD**
P3F

***f* = Filtronic**
1ZD = Lot and Date Code
P2F = Status, Part Code, Part Type
Status: D=Development P = Production
Part Code denotes model (e.g. FPD10000AF)
Part Type: F = FET (pHEMT)

All information and specifications subject to change without notice.

ООО «НИОКРсистемс» - это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование
- Работаем по 275 ФЗ

ООО «НИОКР СИТЕМС»
Москва, 125362, Россия, ул. Вишневая, д. 9, к. 1, Блок 104 а и 104 в

Телефон: 8 (495) 268-14-82
Email: n@nsistems.ru

ИНН: 7735154786
ОГРН: 1167746717709