National Semiconductor

August 2000

LM10
Operational Amplifier and Voltage Reference

General Description

The LM10 series are monolithic linear ICs consisting of a precision reference, an adjustable reference buffer and an independent, high quality op amp.

The unit can operate from a total supply voltage as low as 1.1V or as high as 40V, drawing only 270µA. A complementary output stage swings within 15 mV of the supply terminals or will deliver ±20 mA output current with ±0.4V saturation. Reference output can be as low as 200 mV.

The circuit is recommended for portable equipment and is completely specified for operation from a single power cell. In contrast, high output-drive capability, both voltage and current, along with thermal overload protection, suggest it in demanding general-purpose applications.

The device is capable of operating in a floating mode, independent of fixed supplies. It can function as a remote comparator, signal conditioner, SCR controller or transmitter for analog signals, delivering the processed signal on the same line used to supply power. It is also suited for operation in a wide range of voltage- and current-regulator applications, from low voltages to several hundred volts, providing greater precision than existing ICs.


This series is available in the three standard temperature ranges, with the commercial part having relaxed limits. In addition, a low-voltage specification (suffix "L") is available in the limited temperature ranges at a cost savings.

Features

- input offset voltage: 2.0 mV (max)
- input offset current: 0.7 nA (max)
- input bias current: 20 nA (max)
- reference regulation: 0.1% (max)
- offset voltage drift: 2µV/˚C
- reference drift: 0.002%/˚C

Connection and Functional Diagrams


Metal Can Package (H)



00565201

Order Number LM10BH, LM10CH, LM10CLH or LM10H/883 available per SMA# 5962-8760401
See NS Package Number H08A


Dual-In-Line Package (N)



00565215


Order Number LM10CN or LM10CLN
See NS Package Number N08E

Small Outline Package (WM)



00565217

Order Number LM10CWM or LM10CWMX
See NS Package Number M14B



00565216

© 2004 National Semiconductor Corporation

Absolute Maximum Ratings (Notes 1, 8)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/ Distributors for availability and specifications.

	LM10/LM10B/LM10BL/ LM10C	LM10CL
Total Supply Voltage	45V	7V
Differential Input Voltage (Note 2)	±40V	±7V
Power Dissipation (Note 3)	internally limited	
Output Short-circuit Duration (Note 4)	continuous	
Storage-Temp. Range	−55˚C to +150˚C	
Lead Temp. (Soldering, 10 seconds)		
Metal Can	300˚C	
Lead Temp. (Soldering, 10 seconds) DIP	260˚C	
Vapor Phase (60 seconds)	215˚C	
Infrared (15 seconds)	220˚C	

See AN-450 “Surface Mounting Methods and Their Effect on Product Reliability” for other methods of soldering surface mount devices.

ESD rating is to be determined.

Maximum Junction Temperature

LM10	150˚C
LM10B	100˚C
LM10C	85˚C

Operating Ratings

Package Thermal Resistance

θ_{JA}	
H Package	150˚C/W
N Package	87˚C/W
WM Package	90˚C/W
θ_{JC}	
H Package	45˚C/W

Electrical Characteristics

T_J=25˚C, **$T_{MIN} \le T_J \le T_{MAX}$ (Boldface type refers to limits over temperature range)** (Note 5)

Parameter	Conditions	LM10/LM10B			LM10C			Units
		Min	Typ	Max	Min	Typ	Max	
Input offset voltage			0.3	2.0		0.5	4.0	mV
				3.0			**5.0**	mV
Input offset current (Note 6)			0.25	0.7		0.4	2.0	nA
				1.5			**3.0**	nA
Input bias current			10	20		12	30	nA
				30			**40**	nA
Input resistance		250	500		150	400		kΩ
		150			**115**			kΩ
Large signal voltage gain	V_S=±20V, I_{OUT}=0	120	400		80	400		V/mV
	V_{OUT}=±19.95V	**80**			**50**			V/mV
	V_S=±20V, V_{OUT}=±19.4V	50	130		25	130		V/mV
	I_{OUT}=±20 mA **(±15 mA)**	**20**			**15**			V/mV
	V_S=±0.6V **(0.65V),** I_{OUT}=±2 mA	1.5	3.0		1.0	3.0		V/mV
	V_{OUT}=±0.4V **(±0.3V), V_{CM}=−0.4V**	**0.5**			**0.75**			V/mV
Shunt gain (Note 7)	1.2V **(1.3V)** ≤V_{OUT}≤40V, R_L=1.1 kΩ	14	33		10	33		V/mV
	0.1 mA≤I_{OUT}≤5 mA	**6**			**6**			V/mV
	1.5V≤V^+≤40V, R_L=250Ω	8	25		6	25		V/mV
	0.1 mA≤I_{OUT}≤20 mA	**4**			**4**			V/mV
Common-mode rejection	−20V≤V_{CM}≤19.15V **(19V)**	93	102		90	102		dB
	V_S=±20V	**87**			**87**			dB
Supply-voltage rejection	−0.2V≥V^-≥−39V	90	96		87	96		dB
	V^+=1.0V **(1.1V)**	**84**			**84**			dB
	1.0V **(1.1V)** ≤V^+≤39.8V	96	106		93	106		dB
	V^-=−0.2V	**90**			**90**			dB
Offset voltage drift			2.0			5.0		µV/˚C
Offset current drift			2.0			5.0		pA/˚C
Bias current drift	T_C<100˚C		60			90		pA/˚C

Electrical Characteristics (Continued)

T_J=25˚C, $T_{MIN} \le T_J \le T_{MAX}$ **(Boldface type refers to limits over temperature range)** (Note 5)

Parameter	Conditions	LM10/LM10B			LM10C			Units
		Min	Typ	Max	Min	Typ	Max	
Line regulation	1.2V **(1.3V)** $\le V_S \le$40V		0.001	0.003		0.001	0.008	%/V
	$0 \le I_{REF} \le$1.0 mA, V_{REF}=200 mV			**0.006**			**0.01**	%/V
Load regulation	$0 \le I_{REF} \le$1.0 mA		0.01	0.1		0.01	0.15	%
	$V^+ - V_{REF} \ge$1.0V **(1.1V)**			**0.15**			**0.2**	%
Amplifier gain	0.2V$\le V_{REF} \le$35V	50	75		25	70		V/mV
		23			**15**			V/mV
Feedback sense voltage		195	200	205	190	200	210	mV
		194		**206**	**189**		**211**	mV
Feedback current			20	50		22	75	nA
				65			**90**	nA
Reference drift			0.002			0.003		%/˚C
Supply current			270	400		300	500	µA
				500			**570**	µA
Supply current change	1.2V **(1.3V)** $\le V_S \le$40V		15	**75**		15	**75**	µA

Electrical Characteristics

T_J=25˚C, $T_{MIN} \le T_J \le T_{MAX}$ **(Boldface type refers to limits over temperature range)** (Note 5)

Parameter	Conditions	LM10BL			LM10CL			Units
		Min	Typ	Max	Min	Typ	Max	
Input offset voltage			0.3	2.0		0.5	4.0	mV
				3.0			**5.0**	mV
Input offset current (Note 6)			0.1	0.7		0.2	2.0	nA
				1.5			**3.0**	nA
Input bias current			10	20		12	30	nA
				30			**40**	nA
Input resistance		250	500		150	400		kΩ
		150			**115**			kΩ
Large signal voltage gain	V_S=±3.25V, I_{OUT}=0	60	300		40	300		V/mV
	V_{OUT}=±3.2V	**40**			**25**			V/mV
	V_S=±3.25V, I_{OUT}=10 mA	10	25		5	25		V/mV
	V_{OUT}=±2.75 V	**4**			**3**			V/mV
	V_S=±0.6V **(0.65V),** I_{OUT}=±2 mA	1.5	3.0		1.0	3.0		V/mV
	V_{OUT}=±0.4V **(±0.3V),** V_{CM}=−0.4V	**0.5**			**0.75**			V/mV
Shunt gain (Note 7)	1.5V$\le V^+ \le$6.5V, R_L=500Ω	8	30		6	30		V/mV
	0.1 mA$\le I_{OUT} \le$10 mA	**4**			**4**			V/mV
Common-mode rejection	−3.25V$\le V_{CM} \le$2.4V **(2.25V)**	89	102		80	102		dB
	V_S=±3.25V	**83**			**74**			dB
Supply-voltage rejection	−0.2V$\ge V^- \ge$−5.4V	86	96		80	96		dB
	V^+=1.0V **(1.2V)**	**80**			**74**			dB
	1.0V **(1.1V)** $\le V^+ \le$6.3V	94	106		80	106		dB
	V^-=0.2V	**88**			**74**			dB
Offset voltage drift			2.0			5.0		µV/˚C
Offset current drift			2.0			5.0		pA/˚C
Bias current drift			60			90		pA/˚C
Line regulation	1.2V **(1.3V)** $\le V_S \le$6.5V		0.001	0.01		0.001	0.02	%/V
	$0 \le I_{REF} \le$0.5 mA, V_{REF}=200 mV			**0.02**			**0.03**	%/V

Electrical Characteristics (Continued)

T_J=25˚C, $T_{MIN} \le T_J \le T_{MAX}$ **(Boldface type refers to limits over temperature range)** (Note 5)

Parameter	Conditions	LM10BL			LM10CL			Units
		Min	Typ	Max	Min	Typ	Max	
Load regulation	$0 \le I_{REF} \le 0.5$ mA		0.01	0.1		0.01	0.15	%
	$V^+ - V_{REF} \ge 1.0V$ **(1.1V)**			**0.15**			**0.2**	%
Amplifier gain	$0.2V \le V_{REF} \le 5.5V$	30	70		20	70		V/mV
		20			**15**			V/mV
Feedback sense voltage		195	200	205	190	200	210	mV
		194		**206**	**189**		**211**	mV
Feedback current			20	50		22	75	nA
				65			**90**	nA
Reference drift			0.002			0.003		%/˚C
Supply current			260	400		280	500	µA
				500			**570**	µA

Note 1: Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is functional, but do not guarantee specific performance limits.

Note 2: The Input voltage can exceed the supply voltages provided that the voltage from the input to any other terminal does not exceed the maximum differential input voltage and excess dissipation is accounted for when $V_{IN} < V^-$.

Note 3: The maximum, operating-junction temperature is 150˚C for the LM10, 100˚C for the LM10B(L) and 85˚C for the LM10C(L). At elevated temperatures, devices must be derated based on package thermal resistance.

Note 4: Internal thermal limiting prevents excessive heating that could result in sudden failure, but the IC can be subjected to accelerated stress with a shorted output and worst-case conditions.

Note 5: These specifications apply for $V^- \le V_{CM} \le V^+ - 0.85V$ **(1.0V),** 1.2V **(1.3V)** $< V_S \le V_{MAX}$, V_{REF}=0.2V and $0 \le I_{REF} \le 1.0$ mA, unless otherwise specified: V_{MAX}=40V for the standard part and 6.5V for the low voltage part. Normal typeface indicates 25˚C limits. **Boldface type indicates limits and altered test conditions for full-temperature-range operation;** this is –55˚C to 125˚C for the LM10, –25˚C to 85˚C for the LM10B(L) and 0˚C to 70˚C for the LM10C(L). The specifications do not include the effects of thermal gradients ($\tau_1 \simeq 20$ ms), die heating ($\tau_2 \simeq 0.2$s) or package heating. Gradient effects are small and tend to offset the electrical error (see curves).

Note 6: For $T_J > 90$˚C, I_{OS} may exceed 1.5 nA for $V_{CM} = V^-$. With T_J=125˚C and $V^- \le V_{CM} \le V^- + 0.1V$, $I_{OS} \le 5$ nA.

Note 7: This defines operation in floating applications such as the bootstrapped regulator or two-wire transmitter. Output is connected to the V^+ terminal of the IC and input common mode is referred to V^- (see typical applications). Effect of larger output-voltage swings with higher load resistance can be accounted for by adding the positive-supply rejection error.

Note 8: Refer to RETS10X for LM10H military specifications.

Definition of Terms

Input offset voltage: That voltage which must be applied between the input terminals to bias the unloaded output in the linear region.

Input offset current: The difference in the currents at the input terminals when the unloaded output is in the linear region.

Input bias current: The absolute value of the average of the two input currents.

Input resistance: The ratio of the change in input voltage to the change in input current on either input with the other grounded.

Large signal voltage gain: The ratio of the specified output voltage swing to the change in differential input voltage required to produce it.

Shunt gain: The ratio of the specified output voltage swing to the change in differential input voltage required to produce it with the output tied to the V^+ terminal of the IC. The load and power source are connected between the V^+ and V^- terminals, and input common-mode is referred to the V^- terminal.

Common-mode rejection: The ratio of the input voltage range to the change in offset voltage between the extremes.

Supply-voltage rejection: The ratio of the specified supply-voltage change to the change in offset voltage between the extremes.

Line regulation: The average change in reference output voltage over the specified supply voltage range.

Load regulation: The change in reference output voltage from no load to that load specified.

Feedback sense voltage: The voltage, referred to V^-, on the reference feedback terminal while operating in regulation.


Reference amplifier gain: The ratio of the specified reference output change to the change in feedback sense voltage required to produce it.

Feedback current: The absolute value of the current at the feedback terminal when operating in regulation.

Supply current: The current required from the power source to operate the amplifier and reference with their outputs unloaded and operating in the linear range.


Typical Performance Characteristics (Op Amp)

Input Current




00565218

Common Mode Limits




00565219

Output Voltage Drift




00565220

Input Noise Voltage




00565221

DC Voltage Gain



00565222


Transconductance



00565223


Typical Performance Characteristics (Op Amp) (Continued)

Output Saturation Characteristics




00565224

Output Saturation Characteristics




00565225

Output Saturation Characteristics




00565226

Minimum Supply Voltage




00565227

Minimum Supply Voltage



00565228


Minimum Supply Voltage



00565229


Typical Performance Characteristics (Op Amp) (Continued)

Frequency Response




00565230

Output Impedance




00565231

Typical Stability Range




00565232

Large Signal Response




00565233

Comparator Response Time For Various Input Overdrives



00565234


Comparator Response Time For Various Input Overdrives



00565235


Typical Performance Characteristics (Op Amp) (Continued)

Follower Pulse Response




00565236

Noise Rejection




00565237

Rejection Slew Limiting




00565238

Supply Current




00565239

Thermal Gradient Feedback



00565240


Thermal Gradient Cross-coupling



00565241


Typical Performance Characteristics (Op Amp) (Continued)

Shunt Gain




00565242

Shunt Gain




00565243

Shunt Gain




00565244

Shunt Gain




00565242

Shunt Gain



00565243


Shunt Gain



00565244


Typical Performance Characteristics (Reference)

Line Regulation




00565245

Load Regulation




00565246

Reference Noise Voltage




00565247

Minimum Supply Voltage




00565248

Output Saturation



00565249

Typical Stability Range




00565250

Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages)


Op Amp Offset Adjustment

Standard




00565251

Limited Range



00565252


Limited Range With Boosted Reference



00565253


Positive Regulators (Note 9)

Low Voltage



00565254


Best Regulation



00565255

Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)


Zero Output



00565256


Note 9: Use only electrolytic output capacitors.

Current Regulator



00565257


Shunt Regulator



00565258

Required For Capacitive Loading


Negative Regulator



00565259

*Electrolytic


Precision Regulator



00565260

Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)


Laboratory Power Supply



00565261

*$V_{OUT}=10^{-4}$ R3

HV Regulator




00565262

$$V_{OUT} = \frac{R2}{R1} V_{REF}$$

00565284


Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)

Protected HV Regulator



00565263


Flame Detector



00565264

*800˚C Threshold Is Established By Connecting Balance To V_{REF}.


Light Level Sensor



00565265

*Provides Hysteresis


Remote Amplifier



00565266


Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)

Remote Thermocouple Amplifier



00565267


Transmitter for Bridge Sensor



00565268

Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)


Precision Thermocouple Transmitter



00565269

10 mA≤I_{OUT}≤50 mA
500°C≤T_P≤1500°C
*Gain Trim


Resistance Thermometer Transmitter



00565270

Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)

Optical Pyrometer




00565271

††Level-shift Trim
*Scale Factor Trim
†Copper Wire Wound

$$1\ mA \leq I_{OUT} \leq 5\ mA$$

$$0.01 \leq \frac{I_{D2}}{I_{D1}} \leq 100$$


Thermocouple Transmitter



00565272

$200^{\circ}C \leq T_p \leq 700^{\circ}C$
$1\ mA \leq I_{OUT} \leq 5\ mA$
†Gain Trim

Logarithmic Light Sensor




00565273

$1\ mA \leq I_{OUT} \leq 5\ mA$
‡$50\ \mu A \leq I_D \leq 500\ \mu A$
††Center Scale Trim
†Scale Factor Trim
*Copper Wire Wound


Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)

Battery-level Indicator




00565274

Battery-threshold Indicator



00565275


Single-cell Voltage Monitor



00565276

Flashes Above 1.2V
Rate Increases With
Voltage


Double-ended Voltage Monitor



00565277

Flash Rate Increases
Above 6V and Below 15V

Meter Amplifier




00565278

INPUT
10 mV, 100nA
FULL-SCALE

Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)

Thermometer




00565279

*Trim For Span

†Trim For Zero

Light Meter




00565280

$1 \leq \lambda/\lambda_0 \leq 10^5$

Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)


Microphone Amplifier



00565281

Z_{OUT}~680Ω @ 5 kHz
A_V≤1k
f_1~100 Hz
f_2~5 kHz
R_L~500
*Max Gain Trim

Isolated Voltage Sensor




00565282

†Controls "Loop Gain"
*Optional Frequency Shaping

Typical Applications (Note 10) (Pin numbers are for devices in 8-pin packages) (Continued)

Light-level Controller




Note 10: Circuit descriptions available in application note AN-211.


Application Hints

With heavy amplifier loading to V^-, resistance drops in the V^- lead can adversely affect reference regulation. Lead resistance can approach 1Ω. Therefore, the common to the reference circuitry should be connected as close as possible to the package.

Operational Amplifier Schematic (Pin numbers are for 8-pin packages)




Reference and Internal Regulator (Pin numbers are for 8-pin packages)




00565214

Physical Dimensions inches (millimeters) unless otherwise noted




Metal Can Package (H)
Order Number LM10BH, LM10CH, LM10CLH or LM10H/883
NS Package Number H08A



S.O. Package (WM)
Order Number LM10CWM or LM10CWMX
NS Package Number M14B

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



Dual-In-Line Package (N)
Order Number LM10CN or LM10CLN
NS Package Number N08E

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

BANNED SUBSTANCE COMPLIANCE

National Semiconductor certifies that the products and packing materials meet the provisions of the Customer Products Stewardship Specification (CSP-9-111C2) and the Banned Substances and Materials of Interest Specification (CSP-9-111S2) and contain no "Banned Substances" as defined in CSP-9-111S2.

National Semiconductor
Americas Customer
Support Center
Email: new.feedback@nsc.com
Tel: 1-800-272-9959

www.national.com

National Semiconductor
Europe Customer Support Center
Fax: +49 (0) 180-530 85 86
Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 69 9508 6208
English Tel: +44 (0) 870 24 0 2171
Français Tel: +33 (0) 1 41 91 8790

National Semiconductor
Asia Pacific Customer
Support Center
Email: ap.support@nsc.com

National Semiconductor
Japan Customer Support Center
Fax: 81-3-5639-7507
Email: jpn.feedback@nsc.com
Tel: 81-3-5639-7560

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.

ООО «НИОКРсистемс» - это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование
- Работаем по 275 ФЗ

ООО «НИОКР СИТЕМС»
Москва, 125362, Россия, ул. Вишневая, д. 9, к. 1, Блок 104 а и 104 в

Телефон: 8 (495) 268-14-82
Email: n@nsistems.ru

ИНН: 7735154786
ОГРН: 1167746717709