General purpose (dual digital transistors)

EMH10 / UMH10N

●Structure
Epitaxial planar type
NPN silicon transistor
(Built-in resistor type)

●Features
1) Two DTC123J chips in a EMT or UMT package.
2) Mounting possible with EMT3 or UMT3 automatic mounting machines.
3) Transistor elements are independent, eliminating interference.
4) Mounting cost and area can be cut in half.

●Packaging specifications

	Package	Taping	
	Code	T2R	TN
Type	Basic ordering unit (pieces)	8000	3000
EMH10		◯	–
UMH10N		–	◯


●Absolute maximum ratings (Ta=25°C)

Parameter		Symbol	Limits	Unit
Supply voltage		V_{CC}	50	V
Input voltage		V_{IN}	12	V
			–5	
Output current		I_O	100	mA
		$I_{C\ (Max.)}$	100	mA
Power dissipation	EMH10,UMH10N	Pd	150 (TOTAL)	mW *
Junction temperature		Tj	150	°C
Storage temperature		Tstg	–55~+150	°C

* 120mW per element must not be exceeded.

●Dimensions (Unit : mm)

EMH10





Each lead has same dimensions

Abbreviated symbol : H10

ROHM : EMT6

UMH10N






Each lead has same dimensions

ROHM : UMT6
EIAJ : SC-88

Abbreviated symbol : H10

●Equivalent circuit

EMH10 / UMH10N



R1=2.2kΩ
R2=47kΩ

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Input voltage	$V_{I\ (off)}$	–	–	0.5	V	V_{CC}=5V, I_O=100μA
	$V_{I\ (on)}$	1.1	–	–		V_O=0.3V, I_O=5mA
Output voltage	$V_{O\ (on)}$	–	0.1	0.3	V	I_O/I_I=5mA/0.25mA
Input current	I_I	–	–	3.6	mA	V_I=5V
Output current	$I_{O\ (off)}$	–	–	0.5	μA	V_{CC}=50V, V_I=0V
DC current gain	G_I	80	–	–	–	V_O=5V, I_O=10mA
Transition frequency	f_T	–	250	–	MHz	V_{CE}=10V, I_E= –5mA, f=100MHz *
Input resistance	R_1	1.54	2.2	2.86	kΩ	–
Resistance ratio	R_2/R_1	17	21	26	–	–

* Transition frequency of the device

© 2012 ROHM Co., Ltd. All rights reserved.

●Electrical characteristic curves




Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output current




Fig.4 Output voltage vs. output current

© 2012 ROHM Co., Ltd. All rights reserved.

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.

ROHM SEMICONDUCTOR

Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

http://www.rohm.com/contact/

© 2012 ROHM Co., Ltd. All rights reserved.

ООО «НИОКРсистемс» - это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование
- Работаем по 275 ФЗ

ООО «НИОКР СИТЕМС»
Москва, 125362, Россия, ул. Вишневая, д. 9, к. 1, Блок 104 а и 104 в

Телефон: 8 (495) 268-14-82
Email: n@nsistems.ru

ИНН: 7735154786
ОГРН: 1167746717709